

The **PBM8.350 UM** 8-channel stereo powered mixer with DSP and USB port for MP3 player is designed for professional application. It provides the following features:

PBM8.350 UM

8-Channel Stereo Powered Mixer with DSP, USB port, MP3 player

- Stereo mode: 350W(RMS)@4ohm
400W(EIAJ)@4ohm
180W(RMS)@8ohm
200W(EIAJ)@8ohm
- Bridge mode: 700W@8ohm
- Digital amplifier technology, offering high power and a very dynamic sound.
- 9-band graphic EQ for MAIN/ MONITOR
- 8 MIC/ line in put channels with gold plated XLRs and balanced LINE inputs
- 2 Stereo input channels with balanced TRS jacks
- Ultra-low noise discrete MIC preamps with +48V phantom power
- 3-band equalizer on input channels
- 2 AUX sends for built-in or external effects, on-stage monitor mix, or head phone mixing
- 256 position multi-effect
- 2-track recording IN/OUT (phono)
- Head phone output
- Output connector: 6.3 ϕ jack+ 4-way speak on
- USB port for MP3 Player
- Dimensions (WxDxH): 550 x 220 x 310 mm(21.65" x 8.66" x 12.2")
- Net Weight: 7.8kg (17.2lbs)

